展开尺寸：240x105mm 做四折页, 折后尺寸 60X105mm,80g普通纸正反双面单色印刷

105mm

60mm | 60mm | 60mm | 60mm

LIFEnSOUL



IE101 User manual
Waterproof Bluetooth Shower Speaker

Thank you for choosing our product. We hope you will enjoy it very much.

Safety Instructions
Read this manual carefully before putting the appliance into operation and keep this manual for future reference.
-Keep the device away from heat, direct sunlight and sharp edges.
- Keep the device away from open flames.
-Do not insert any metal object into the device. Risk of short circuit!
-To avoid a static charge, do not use the device in an extremely dry climate.
- Do not repair the unit yourself. Contact an authorized specialist if needed

Product Overview





DC5V

Accessories included:
1.USB charging cable

Charge Integrated Battery
"This Bluetooth Speaker is powered by an integrated rechargeable lithium battery."
1.When the LED indicator light turns red, the battery is being charged.
2.When the red LED indicator light turns off, the battery is fully charged.

Pairing
When Bluetooth Speaker is in power off mode, press and hold the on/off button for about 6 seconds until the red LED and blue LED are flashing alternatively. Now the speaker is ready for pairing.

Tips:
Please make sure the speaker is in power off mode when trying to activate the pairing mode.

1.Turn on our mobile phone and activate the Bluetooth function.
2.Searching for Bluetooth device IE 101 will show up.
3.Pair your device with IE101 if password is needed, type in "0000". After IE101 is paired with your device, connect it to your device.

Tips
Once this speaker is paired and connected to your mobile phone, the next time speaker is turned on, it will automatically pair back to the last paired device, as long as the last paired device's Bluetooth setting is turned on.

Button description
On/Off: to switch on or off the unit.
⏮ Short press for the previous song. Long press to turn down the volume.
⏭ Short press for the next song. Long press to turn up the volume.
⏯ Play/ pause the music.
Phone: to pick up or hang up a phone call

Notes and tips:
1.You can press Phone button twice quickly to redial the last phone call.

Trouble shooting

Problem	Causes	Solutions
Cannot switch the speaker on	Battery empty	Charge the battery
Unable to pair the speaker	Speaker is already switched on, and it is not in pairing mode	Refer to the section of paring IE101 to mobile phone or other device

Technical
* Waterproof Bluetooth speaker
* Comply with Bluetooth V2.1
* RF range: 10M
* Frequency response: 100HZ-20KHZ
* Output: 3W
* S/N Ratio: >75db
* Distortion: <1.0%
* Standby time: 8-10 hours
* Charging time: approx. 3 hours
* Playing time: approx. 6hours
* With 500mah BL-5C Lithium Battery.

CE FC

LIFEnSOUL

www.lifensoul.com

240mm